

340-Watt 7.1 Surround Sound Karaoke Receiver with HDMI Switch & Up Conversion

The Only Karaoke Receiver/Amplifier with Mic Audio through HDMI





Features

- 3 HDMI Inputs and 1 HDMI Output 1 Front Panel HDMI Input for convenience
- Up-Conversion 3 RCA AV Input is upconverted to HDMI 1080p Output
- 1 Front-Panel RCA Audio/Video Aux Input to easily connect your portable device.
- iPad®, iPod® and tablet ready with a front USB power connector that supplies 2A of power for tablets or USB powered devices.
- Utilizes the latest chip that is capable of decoding most of the popular audio formats
- Multiple Audio Modes (RCA Only): Can be set to 2 channels, 3.1 channels, 5.1 channels or 7.1 channels surround sound mode for home theater
- Exclusive Karaoke 3.1 channels, 5.1 channels or 7.1 channels mode allow users to fill all speakers with the same output as the front right and front left speakers.

Specifications

- 3 Standard ¼" Microphone Inputs: 2 Front, 1 in Rear with individual volume controller
- 1 AM/FM Radio Tuner with Antenna Connector for AM/FM Band
- Optical Input and Coaxial Input
- 1 Front Panel RCA Audio/Video Input
- 1 Front Panel HDMI Input
- 1 3.5mm Headphone Jack Output
- 1 Composite Video Output with HDMI down conversion function to see HDMI video in 480p
- Power Output:
 - Front Speakers 80 Watts x 2 RMS
 - Center Speaker: 80 Watts RMS
 - Surround Speakers: 25 Watts x 4 RMS
- 110V/220V Voltage Switch
- Dimensions: 17.1"W x 17.32"D x 6.25"H
- 1 Year Manufacturer Warranty
- · Designed in the U.S.A.

Receiver Functions

- 8 DSP Sound Effects
- Large VFD Display
- 1 L/R Record Output
- 7 Speakers Banana Output
- Subwoofer Output via RCA Output
- AM/FM Radio Turner with 10 Pre-Set Station for each Band
- · Auto Station Scan for FM/AM Radio

Karaoke Functions

- Master Music VolumeControl
- 3 Microphone Inputs: 2 in front, and 1 in rear (ideal for wireless mics)
- 3 Individual Microphone Volume Controllers

Includes

- Remote Control
- 2 AA Batteries
- Power Cord