

Acesonic® KJV-835

400 Watt Karaoke Mixing Amplifier with 3.5" LCD Monitor, Recorder and MP3G Player

The DJ's Ultimate Sidekick!



Features:

- **Built-in Dual A/V Outputs Switches with a 3.5" LCD Monitor.** The first A/V switch is to set the output for the singer's monitor and the second A/V switch is to set the output of the built-in LCD monitor and the headphone jack. No need for a TV when performing, just use the 3.5" LCD monitor to see your karaoke tracks.
- **Built-in MP3G Recorder and Player Module.** This can digitally record all of your performances in MP3 or MP3G format. The MP3G module also plays MP3G files stored in SD Cards
- **Built-in USB Port.** Lets you play your music and record your performance digitally from and to your PC or Mac. You can turn your laptop into a karaoke player and connect it to the mixing amplifier for audio output. Instantly capture the audio signal in either MP3 or WAV format and share with your friends.
- 400 Watt Max Power Output
- 3.5" Built-In LCD Screen to monitor a 2nd A/V source
- Headphone Output for 2nd A/V source
- LCD Status Screen to Display: Key, Main Input Source, Monitor Input Source and Multiplex
- Built-in MP3G Recorder and Player Module
- 4 Audio/Video Inputs: DVD/AUX/PC/MP3G Module
- 2 Component Video Inputs: DVD/AUX and 1 Component Video Output
- 1 RCA Audio/Video Output
- 1 PC Input (Composite Video + USB Port)
- Auto Input Selector
- L/R Multiplex Channel Output Selector
- Music Low, Mid, High, Balance, Volume Controls
- Microphone Delay, Repeat, Echo, Low, High Volume Controls
- Microphone Volume Controls for Low, Mid, High, Echo, Balance Volume
- 3 Front & 2 Rear 1/4" Microphone Inputs
- Master Microphone Control
- Master Echo Control
- Master Volume Control
- 4 Audio Outputs (Record Out, Line Out, Subwoofer Out (Music/ Mixing), Mic Out (High/Low)
- 2 Banana Plug Speaker Connectors
- 115/230 Voltage for Worldwide Compatible
- Built-in BBE Sonic Maximizer for both vocal and music
- True Vocal Cancellation Function to remove up to 90% of lead vocals
- Temperature-Active, Ultra-Low-Noise Fan for non-stop operation
- 2 SpeakOn Speaker Connectors
- Pre-Input and Pre-Output for External Effort

Specifications:

- Integrated USB Audio Solution using C-Media CM106 Audio I/O Controller works for PC and Mac
- Maximum Output: 200W + 200W @ 8 Ohms Max
- Microphone Input Sensitivity: <20mV
- Music Input Sensitivity: 250mV / 47K Ohms / 1kHz
- Microphone Frequency Response: 20Hz - 20 kHz / 3dB
- Music Frequency Response: 20Hz - 20 kHz / 3dB
- Microphone EQ characteristics: Treble: +/- 10dB (10kHz), Bass: +/- 10dB (100Hz)
- Music EQ characteristics: Treble: +/- 10dB (10kHz), Bass: +/- 10dB (100Hz)
- Key Control Range +/- 6 Half Tones
- Speaker Wattage Impedance: 4 Ohm - 8 Ohm
- Voltage: AC 115V - 230V Manual Select

System Includes:

- 1 Remote Control
- 16 ft USB Cable
- RCA Cable
- USB Driver Disc
- 2 AAA Batteries
- Rack Mount Kit

For more info, go to
www.acesonic.com