

Acesonic® KM-360

Professional Digital Mixer
with Feedback & Vocal eliminator,
PC Interface, and Microphone Noise Gate

Powerful, Versatile, Heavy-Duty Mixer



Features:

- **Feedback Eliminator** - Suppresses feedback noise from speakers.
- **Vocal Eliminator** - Takes out up to 90% of vocals.
- **Music Volume Auto Leveling** - Boosts up audio when it's too low and decreases it when it's too loud.
- **Digital Effect Processor** - Powerful built-in Reverb and Echo Effects that can dramatically increase the quality of your performance
- **3-Band Music and 5-Band Microphone Equalizer**
- **Microphone Noise Gate** - Auto-mute function enables your mixer to automatically turn off the microphone when it is not in-use.
- **Multiple-Channel Surround Sound Configuration** - additional audio signal outputs for center speaker (C), sub-woofer (S), and 2 rear speakers (SR)
- **5 Microphone Inputs with 2 XLR Input Connectors** - 3 microphone inputs in the front and 2 balanced audio connectors (XLR) for high quality microphone signal inputs from the rear
- **S/PDIF Digital Input** - Sends the purest audio signal to the mixer without any RF interference noise.
- **RS-232 Serial Port PC Interface** - Serial port for PC connections.
- **User Lock-Down Mode** - Prevents other users from changing any of your own settings.
- **Subwoofer Signal Control** - 3 powerful subwoofer settings to fine tune your subwoofer's performance.
- **Center Speaker and Rear Speakers Signal Control** - Enables you to independently control the volume of your center and surrounding speakers plus also control the balance between music and vocals.
- **Music and Microphone Balance** - Designed for you to compensate for irregular room configurations to achieve sound balance throughout the space.
- **Auto-Source Detection** - A built-in function that enables the mixer to automatically play music and video from one of the 3 available inputs.
- **4 Preset Memory Recall Buttons** - Save all of your optimal setting to one of the 4 preset memory buttons.
- **XLR Line Outputs** - Line outputs including Left, Right, Center and Subwoofer audio signal are using XLR Balanced Audio Connectors to preserve the cleanest signal to your professional amplifier.

Specifications:

- 11-Step Digital Key Controller with 1/2 Tone Per Step
- Support digital S/PDIF input (PCM 44.1KHz, 48KHz)
- 4 RCA A/V inputs & 2 RCA A/V outputs
- 1 RCA Record output & 1 RCA Surround Sound Output
- 1 External Remote Control Signal Input
- 1 U Rack Mountable
- 1 Year Manufacturer Warranty
- Net weight: 8lbs
- Dimension: 16.75" (L) x 4.5" (W) x 1.75" (H)

System Includes:

- 1 Remote control
- Power Cable

For more info, go to
www.acesonic.com